

REFERENCE

608-, 618-, 634-, 635-, 636-, 637-, 638-, 639-, 682-, AND 683-TYPE TELEPHONE SETS

IDENTIFICATION

1. GENERAL

1.01 This section contains information on 600-series CALL DIRECTOR® telephone sets.

1.02 This section is reissued to:

- Show 634DAM, 635DAM, 636CAM, 637DAM, 638CAM, 639DAM, 682AAM, and 683AAM sets MD
- Add 634DAMS1, 635DAMS1, 636CAMS1, 637DAMS1, 638CAMS1, 639DAMS1, 682AAMS1, and 683AAMS1 code sets.

1.03 ♦All four letter coded sets are furnished from the factory in only the numerical code (1), and all other numerical coded sets are rated MD. Sets can be equipped with different modular key arrangements by ordering the appropriate 635-, 658-type key, or 76A lamp socket. Refer to the appropriate table in this section for recommended layout arrangements of field-installed keys.

1.04 The 634DAMS1, 635DAMS1, 636CAMS1, 637DAMS1, 638CAMS1, 639DAMS1, 682AAMS1, and 683AAMS1 sets are furnished equipped with a new line switch which breaks both the tip and ring side of the line instead of the ring side only.♦

1.05 Early models designated with a single letter code (A, B, C, or D) are equipped with 598-, 599-, 656-, or 657-type keys using a KS-type connector. Later models designated by a double letter (AA, CA, or DA) and triple letter (AAM, CAM, or DAM) are equipped with 635-type keys using 508- or 509-type plugs. The 598- and 599-type keys are electrically and mechanically interchangeable with the 656- and 657-type. None of these keys, however, are compatible with the 635-type keys

and cannot be intermixed. Current production 635-type keys have been modified for easy lamp replacement. Remove lamp cap and insert 553C tool through hole in top of button. In early production keys, it was necessary to remove faceplate, key collar, and button to change lamps.

1.06 All triple and four letter coded sets (modular) are furnished from the factory equipped with a G15A handset, H4DU handset cord, and 616E jack assembly. Early model (nonmodular) single and double letter code sets were furnished equipped with a G3-type handset and cord.

1.07 All single, double, and triple letter coded sets are rated MD and will be replaced by modular four letter coded sets, respectively, except for the 608C and 618B sets which will be replaced by the 682AAMS1 and 683AAMS1 sets, respectively.

2. IDENTIFICATION

2.01 The faceplate assemblies listed in Tables C through G consist of a faceplate and three mats; one each in Silver (-78), Gold (-79), and the coordinated color. The coordinated color suffix is found in Table B.

2.02 Table A lists the major features of these CALL DIRECTOR telephone sets, refer to Table B for ordering information.

2.03 The 667B (MD) transmitter may be modified with the D-180196 Kit of Parts to reduce pickup due to mechanical vibrations.

2.04 Ringer volume control is in two steps. A third step to silence the ringer is blocked by a stop screw which can be removed.

NOTICE

Not for use or disclosure outside the
Bell System except under written agreement

SECTION 502-601-101

2.05 The 811218585 blocking rings or 812365948 button stops are no longer shipped loose with each set. These items must be ordered separately if required.

2.06 Current production telephone sets are equipped with a satin-silver (-87) mounting cord.

2.07 Current production telephone sets are factory-equipped with a KS-20419L1 (10 volt ac only) buzzer. Provisions are made for mounting one KS-8109L2 buzzer when an additional buzzer is desired.

3. TABLE INDEX

Table A—Major Features

Table B—Ordering Guide

Table C—Faceplates and Mats For 608- and 618-Type Telephone Sets

Table D—Faceplates and Mats For 634- and 635-Type Telephone Sets

Table E—Faceplates and Mats For 636- and 637-Type Telephone Sets

Table F—Faceplates and Mats For 638- and 639-Type Telephone Sets

Table G—Faceplates and Mats for 682- and 683-Type Telephone Sets

Table H—Bezel and Housing Assembly

Table I—Replaceable Components

Table J—Key Arrangements—18-Button Single Letter (MD) Code Sets

Table K—Key Arrangements—18-Button Double Letter (MD), Triple Letter (MD), and Four Letter Code Sets

Table L—Key Arrangements—30-Button Single Letter (MD) Code Sets

Table M—Key Arrangements—30-Button Double Letter (MD), Triple Letter (MD), and Four Letter Code Sets

Table N—Key Identification

◆ TABLE A ◆

MAJOR FEATURES

SET CODE FEATURE	608	618	634	635	636	637	638	639	682	683
18-Button		•	•		•		•		•	
30-Button	•			•		•		•		•
2-/4-Wire Operation	•	•							•	•
Handset/Headset Operation	•	•			•	•	•	•	•	•
Concentrator			•	•			•	•		
Speakerphone	•	•	•	•					•	•
1A KTS					•	•				
1A1, 1A2, 6A, and 6B KTS	•	•	•	•	•	•	•	•	•	•

◆ TABLE B ◆

ORDERING GUIDE

TELEPHONE SET CODE	TELEPHONE SET COLOR	COLOR SUFFIX	MATS	COLOR SUFFIX
			COORDINATED COLOR	
634DAMS1	Black	(-03)	Charcoal	(-70)
635DAMS1	Green	(-51)	Light Green	(-71)
636CAMS1	Yellow	(-56)	Light Yellow	(-72)
637DAMS1	White	(-58)	Light Gray	(-73)
638CAMS1	Light Beige	(-60)	Muted Beige	(-75)
639DAMS1	Aqua Blue	(-62)	Muted Blue	(-76)
682AAMS1	Any Color Tel Set (Note)		Silver	(-78)
683AAMS1			Gold	(-79)

Note: Silver or Gold mats can be used with any color telephone set.

TABLE C
FACEPLATES AND MATS FOR 608- AND 618-TYPE TELEPHONE SETS

TEL SET	SET CODE	FACEPLATE ASSEMBLY	FACEPLATE ONLY	MATS*, †
608B, C	3, 12, 17, 20	21G1-	812066157 (P-20F615)	818861700 (P-88F170) 818861718 (P-88F171) 818861726 (P-88F172) 818861734 (P-88F173) 818861759 (P-88F175) 818861767 (P-88F176) 818861783 (P-88F178) 818861791 (P-88F179)
		21M1	812066199 (P-20F619)	818668709 (P-86F870) 818668717 (P-86F871) 818668725 (P-86F872) 818668733 (P-86F873) 818668758 (P-86F875) 818668766 (P-86F876) 818668782 (P-86F878) 818668790 (P-86F879)
618A, B	2, 7, 11, 13	20E1-	812066041 (P-20F604)	818860702 (P-88F070) 818860710 (P-88F071) 818860728 (P-88F072) 818860736 (P-88F073) 818860751 (P-88F075) 818860769 (P-88F076) 818860785 (P-88F078) 818860793 (P-88F079)
		20G1-	812066066 (P-20F606)	818669707 (P-86F970) 818669715 (P-86F971) 818669723 (P-86F972) 818669731 (P-86F973) 818669756 (P-86F975) 818669764 (P-86F976) 818669780 (P-86F978) 818669798 (P-86F979)

*Seventh and eighth digits of comcode number designate color code as shown in Table B

†Last two digits of P-number designate color code as shown in Table B

♦TABLE D♦
FACEPLATES AND MATS FOR 634- AND 635-TYPE TELEPHONE SETS

TEL SET	SET CODE	FACEPLATE ASSEMBLY	FACEPLATE ONLY	MATS*, †
634A, B, C, D	1, 2, 6, 7, 9, 10	20A1-	812066009 (P-20F600)	818060709 (P-80F070) 818060717 (P-80F071) 818060725 (P-80F072) 818060733 (P-80F073) 818060758 (P-80F075) 818060766 (P-80F076) 818060782 (P-80F078) 818060790 (P-80F079)
	4	20B1-	812066017 (P-20F601)	818661704 (P-86F170) 818661712 (P-86F171) 818661720 (P-86F172) 818661738 (P-86F173) 818661753 (P-86F175) 818661761 (P-86F176) 818661787 (P-86F178) 818661795 (P-86F179)
	11, 13	20C1-	812066025 (P-20F602)	828230706 (P-82L070) 828230714 (P-82L071) 828230722 (P-82L072) 828230730 (P-82L073) 828230755 (P-82L075) 828230763 (P-82L076) 828230789 (P-82L078) 828230797 (P-82L079)
	12	20D1-	812066033 (P-20F603)	828231704 (P-82L170) 828231712 (P-82L171) 828231720 (P-82L172) 828231738 (P-82L173) 828231753 (P-82L175) 828231761 (P-82L176) 828231787 (P-82L178) 828231797 (P-82L179)
634DA, 634DAM, 634DAMS1	1, 2, 4, 6, 7	20R1-	802697003 (P-269700)	818664708 (P-86F470) 818664716 (P-86F471) 818664724 (P-86F472) 818664732 (P-86F473) 818664757 (P-86F475) 818664765 (P-86F476) 818664781 (P-86F478) 818664799 (P-86F479)
	11, 12, 13	20S1-	802697011 (P-269701)	818665705 (P-86F570) 818665713 (P-86F571) 818665721 (P-86F572) 818665739 (P-86F573) 818665754 (P-86F575) 818665762 (P-86F576) 818665788 (P-86F578) 818665796 (P-86F579)
635A, C, D	1, 2, 3, 10, 11, 12	21A1-	812066090 (P-20F609)	818665705 (P-86F570) 818665713 (P-86F571) 818665721 (P-86F572) 818665739 (P-86F573) 818665754 (P-86F575) 818665762 (P-86F576) 818665788 (P-86F578) 818665796 (P-86F579)
	4	21B1-	812066108 (P-20F610)	
	16, 17	21C1-	812066116 (P-20F611)	
	18	21D1-	812066124 (P-20F612)	

◆TABLE D (Contd)◆
FACEPLATES AND MATS FOR 634- AND 635-TYPE TELEPHONE SETS

TEL SET	SET CODE	FACEPLATE ASSEMBLY	FACEPLATE ONLY	MATS*, †
635DA, 635DAM, 635DAMS1	1, 2, 3, 4, 10, 11, 12	21R1-	802697029 (P-269702)	828234708 (P-82L470) 828234716 (P-82L471) 828234724 (P-82L472) 828234732 (P-82L473) 828234757 (P-82L475) 828234765 (P-82L476) 828234781 (P-82L478) 828234799 (P-82L479)
	16, 17, 18	21S1	802697037 (P-269703)	828235705 (P-82L570) 828235713 (P-82L571) 828235721 (P-82L572) 828235739 (P-82L573) 828235754 (P-82L575) 828235762 (P-82L576) 828235788 (P-82L578) 828235796 (P-82L579)

*Seventh and eight digits of comcode number designate color code as shown in Table B

†Last two digits of P-number designate color code as shown in Table B

♦ **TABLE E** ♦
FACEPLATES AND MATS FOR 636- AND 637-TYPE TELEPHONE SETS

TEL SET	SET CODE	FACEPLATE ASSEMBLY	FACEPLATE ONLY	MATS*, †
636A, B, C	1, 2, 6, 7, 9, 10	20E1-	812066041 (P-20F604)	818860702 (P-88F070) 818860710 (P-88F071) 818860728 (P-88F072)
	4	20F1-	812066058 (P-20F605)	818860736 (P-88F073) 818860751 (P-88F075) 818860769 (P-88F076)
	14, 15	20H1-	812066074 (P-20F607)	818860785 (P-88F078) 818860793 (P-88F079)
636CA, 636CAM, 636CAMS1	1, 2, 4, 6, 7, 14, 15	20T1-	802697086 (P-269708)	828238709 (P-82L870) 828238717 (P-82L871) 828238725 (P-82L872) 828238733 (P-82L873) 828238758 (P-82L875) 828238766 (P-82L876) 828238782 (P-82L878) 828238790 (P-82L879)
637A, C, D	1, 2, 3, 10, 11, 12, 13, 14, 15	21G1-	812066157 (P-20F615)	818861700 (P-88F170) 818861718 (P-88F171)
	4	21H1-	812066165 (P-20F616)	818861726 (P-88F172) 818861734 (P-88F173)
	5	21J1-	812066173 (P-20F617)	818861759 (P-88F175) 818861767 (P-88F176)
	9, 19	21K1-	812066181 (P-20F618)	818861783 (P-88F178) 818861791 (P-88F179)
637DA, 637DAM, 637DAMS1	1, 2, 3, 4, 5, 9, 10, 11, 12, 19	21T1-	802697102 (P-269710)	828332700 (P-83L270) 828332718 (P-83L271) 828332726 (P-83L272) 828332734 (P-83L273) 828332759 (P-83L275) 828332767 (P-83L276) 828332783 (P-83L278) 828332791 (P-83L279)

*Seventh and eight digits of comcode number designate color code as shown in Table B

†Last two digits of P-number designate color code as shown in Table B

♦TABLE F♦
FACEPLATES AND MATS FOR 638- AND 639-TYPE TELEPHONE SETS

TEL SET	SET CODE	FACEPLATE ASSEMBLY	FACEPLATE ONLY	MATS*, †
638A, B, C	1, 2, 6, 7, 9, 10	20E1-	812066041 (P-20F604)	818860702 (P-88F070) 818860710 (P-88F071) 818860728 (P-88F072) 818860736 (P-88F073) 818860751 (P-88F075)
	4	20F1-	812066058 (P-20F605)	818860769 (P-88F076) 818860785 (P-88F078) 818860793 (P-88F079)
638CA, 638CAM, 638CAMS1	1, 2, 4, 6, 7	20T1-	802697086 (P-269708)	828238709 (P-82L870) 828238717 (P-82L871) 828238725 (P-82L872) 828238733 (P-82L873) 828238758 (P-82L875) 828238766 (P-82L876) 828238782 (P-82L878) 828238790 (P-82L879)
639A, C, D ‡	1, 2, 3, 10, 11, 12, 15	21G1-	812066157 (P-20F615)	818861700 (P-88F170) 818861718 (P-88F171)
	4	21H1-	812066165 (P-20F616)	818861726 (P-88F172) 818861734 (P-88F173)
	5	21J1-	812066173 (P-20F617)	818861759 (P-88F175) 818861767 (P-88F176)
	9	21K1-	812066181 (P-20F618)	818861783 (P-88F178) 818861791 (P-88F179)
639DA, 639DAM, 639DAMS1	1, 2, 3, 4, 10, 11, 12	21T1-	802697102 (P-269710)	828332700 (P-83L270) 828332718 (P-83L271) 828332726 (P-83L272) 828332734 (P-83L273) 828332759 (P-83L275) 828332767 (P-83L276) 828332783 (P-83L278) 828332791 (P-83L279)

*Seventh and eight digits of comcode number designate color code as shown in Table B

†Last two digits of P-number designate color code as shown in Table B

‡639C, D sets not available in 5, 9, 15 code

♦TABLE G♦
FACEPLATES AND MATS FOR 682- AND 683-TYPE TELEPHONE SETS

TEL SET	SET CODE	FACEPLATE ASSEMBLY	FACEPLATE ONLY	MATS*, †
682AA, 682AAM, 682AAMS1	1, 2, 6, 7	20T1-	802697086 (P-269708)	828238709 (P-82L870) 828238717 (P-82L871) 828238725 (P-82L872) 828238733 (P-82L873) 828238758 (P-82L875) 828238766 (P-82L876) 828238782 (P-82L878) 828238790 (P-82L879)
	11, 13	20U1-	802697094 (P-269709)	828239707 (P-82L970) 828239715 (P-82L971) 828239723 (P-82L972) 828239731 (P-82L973) 828239756 (P-82L975) 828239764 (P-82L976) 828239780 (P-82L978) 828239798 (P-82L979)
683AA, 683AAM, 683AAMS1	1, 2, 3, 4, 5, 9, 10, 11, 12, 19	21T1-	802697102 (P-269710)	828332700 (P-83L270) 828332718 (P-83L271) 828332726 (P-83L272) 828332734 (P-83L273) 828332759 (P-83L275) 828332767 (P-83L276) 828332783 (P-83L278) 828332791 (P-83L279)
	17	21U1-	802697110 (P-269711)	828333708 (P-83L370) 828333716 (P-83L371) 828333724 (P-83L372) 828333732 (P-83L373) 828333757 (P-83L375) 828333765 (P-83L376) 828333781 (P-83L378) 828333799 (P-83L379)

*Seventh and eight digits of comcode number designate color code as shown in Table B

†Last two digits of P-number designate color code as shown in Table B

◆TABLE H◆

BEZEL AND HOUSING ASSEMBLY

TEL SET	BEZEL ASSY (NOTES 1 AND 2)	HOUSING ASSY*, †
608B	811159953 (P-11E995)	828119032 (P-81J903) 828119511 (P-81J951) 828119560 (P-81J956) 828119586 (P-81J958) 828119602 (P-81J960) 828119628 (P-81J962)
608C	812652121 (P-26E212)	818433039 (P-84C303) 818433518 (P-84C351) 818433567 (P-84C356) 818433583 (P-84C358) 818433609 (P-84C360) 818433625 (P-84C362)
618A	811159946 (P-11E994)	828118034 (P-81J803) 828118513 (P-81J851) 828118562 (P-81J856) 828118588 (P-81J858) 828118604 (P-81J860) 828118620 (P-81J862)
618B	814455085 (P-44E508)	818432031 (P-84C203) 818432510 (P-84C251) 818432569 (P-84C256) 818432585 (P-84C258) 818432601 (P-84C260) 818432627 (P-84C262)
634A, B, C, D		818430035 (P-84C003) 818430514 (P-84C051) 818430563 (P-84C056) 818430589 (P-84C058) 818430605 (P-84C060) 818430621 (P-84C062)
634DA		840473037 840473516 840473565 840473581 840473607 840473623
634DAM,634DAMS1	814455085 (P-44E508)	840712012 (Black) 840712020 (Green) 840712038 (Yellow) 840712046 (White) 840712053 (Beige) 840712061 (Aqua Blue)
635A, C, D	812652121 (P-26E212) or 840155642	818431033 (P-84C103) 818431512 (P-84C151) 818431561 (P-84C156) 818431587 (P-84C158) 818431603 (P-84C160) 818431629 (P-84C162)

♦TABLE H (Cont)♦

BEZEL AND HOUSING ASSEMBLY

TEL SET	BEZEL ASSY (NOTES 1 AND 2)	HOUSING ASSY*, †
635DA	840155642	840474035 840474514 840474563 840474589 840474605 840474621
635DAM,635DAMS1		840712269 (Black) 840712277 (Green) 840712285 (Yellow) 840712293 (White) 840712301 (Beige) 840712319 (Aqua Blue)
636A, B, C	814455085 (P-44E508)	828118034 (P-81J803) 828118513 (P-81J851) 828118562 (P-81J856) 828118588 (P-81J858) 828118604 (P-81J860) 828118620 (P-81J862)
636CA		828534032 (P-85L403) 828534511 (P-85L451) 828534560 (P-85L456) 828534586 (P-85L458) 828534602 (P-85L460) 828534628 (P-85L462)
636CAM,636CAMS1		840712517 (Black) 840712525 (Green) 840712533 (Yellow) 840712541 (White) 840712558 (Beige) 840712566 (Aqua Blue)
637A, C, D	812652121 (P-26E212) or 840155642	828119032 (P-81J903) 828119511 (P-81J951) 828119560 (P-81J956) 828119586 (P-81J958) 828119602 (P-81J960) 828119628 (P-81J962)
637DA	840155642	828535039 (P-85L503) 828535518 (P-85L551) 828535567 (P-85L556) 828535583 (P-85L558) 828535609 (P-85L560) 828535625 (P-85L562)
637DAM,637DAMS1	840155642	840712764 (Black) 840712772 (Green) 840112780 (Yellow) 840712798 (White) 840712806 (Beige) 840712814 (Aqua Blue)

◆TABLE H (Cont)◆

BEZEL AND HOUSING ASSEMBLY

TEL SET	BEZEL ASSY (NOTES 1 AND 2)	HOUSING ASSY*, †
638A, B, C	814455085 (P-44E508)	828118034 (P-81J803) 828118513 (P-81J851) 828118562 (P-81J856) 828118588 (P-81J858) 828118604 (P-81J860) 828118620 (P-81J862)
638CA	814455085 (P-44E508)	828534032 (P-85L403) 828534511 (P-85L451) 828534560 (P-85L456) 828534586 (P-85L458) 828534602 (P-85L460) 828534628 (P-85L462)
638CAM,638CAMS1		840712517 (Black) 840712525 (Green) 840712533 (Yellow) 840712541 (White) 840712558 (Beige) 840712566 (Aqua Blue)
639A, C, D	812652121 (P-26E212) or 840155642	828119032 (P-81J903) 828119511 (P-81J951) 828119560 (P-81J956) 828119586 (P-81J958) 828119602 (P-81J960) 828119628 (P-81J962)
639DA	840155642	828535039 (P-85L503) 828535518 (P-85L551) 828535567 (P-85L556) 828535583 (P-85L558) 828535609 (P-85L560) 828535625 (P-85L562)
639DAM,639DAMS1,		840712764 (Black) 840712772 (Green) 840712780 (Yellow) 840712798 (White) 840712806 (Beige) 840712814 (Aqua Blue)
682AA	814455085 (P-44E508)	828534032 (P-85L403) 828534511 (P-85L451) 828534560 (P-85L456) 828534586 (P-85L458) 828534602 (P-85L460) 828534628 (P-85L462)
682AAM,682AAMS1		840712517 (Black) 840712525 (Green) 840712533 (Yellow) 840712541 (White) 840712558 (Beige) 840712566 (Aqua Blue)

◆TABLE H (Cont)◆

BEZEL AND HOUSING ASSEMBLY

TEL SET	BEZEL ASSY (NOTES 1 AND 2)	HOUSING ASSY*, †
683AA	840155642	828535039 (P-85L503) 828535518 (P-85L551) 828535567 (P-85L556) 828535583 (P-85L558) 828535609 (P-85L560) 828535625 (P-85L562)
683AAM,683AAMS1		840712764 (Black) 840712772 (Green) 840712780 (Yellow) 840712798 (White) 840712806 (Beige) 840712814 (Aqua Blue)

* Seventh and eighth digits of comcode number designate color code as shown in Table B unless otherwise specified.

† Last two digits of P-number designate color as shown in Table B.

Notes:

1. Components of 814455085 (P-44E508) bezel assembly:

- 814455051 (P-44E505) Upper Bezel
- 814455069 (P-44E506) Lower Bezel
- 814455077 (P-44E507) Bezel Retainer
- 997126610 (RM-712661) Bezel Clip
- 840993778 Bezel Spring

2. Components of 840155642 bezel assembly:

- 834080939 (P-404093) Upper Bezel
- 834080947 (P-404094) Lower Bezel
- 814455077 (P-44E507) Bezel Retainer
- 997126610 (RM-712661) Bezel Clip
- 840993778 Bezel Spring

◆ TABLE I ◆

REPLACEABLE COMPONENTS

TELEPHONE SET	MTG CORD	DIAL (Note)	RINGER	HANDSET*†
608B, C	D200F-87	8R-58 8RA-58 8C-58 or 8CA-58	N1A or T1A	G3-Type or G15A
618A, B	D120C-87			
634A, B, C, D	D50L-87			
634DA, DAM, DAMS1	D50BD-87			
635A, C, D	D80B-87			
635DA, DAM, DAMS1	D80E-87			
636A, B, C	D120C-87			
636CA, CAM, CAMS1	D120M-87			
637A, C, D	D200F-87			
637DA, DAM, DAMS1	D200AA-87			
638A, B, C	D50L-87			
638CA, CAM, CAMS1	D50BD-87			
639A, C, D	D80B-87			
639DA, DAM, DAMS1	D80E-87			
682AA, AAM, AAMS1	D120M-87	8C-58 or 8CA-58		
683AA, AAM, AAMS1	D200AA-87	8C-58 or 8CA-58		

Note: Sets to be used with speakerphone must be equipped with an 8C or 8CA dial.

* Color suffix from Table B must be added.

† Single and double letter coded sets are equipped with G3-type handset and cord. Triple and four letter coded sets are equipped with G15A handset, H4DU handset cord, and 616E jack assembly.

♦TABLE J♦
KEY ARRANGEMENTS- 18 BUTTON SINGLE LETTER (MD) CODE SETS (NOTE 1)

TELEPHONE SET		1ST MODULE	2ND MODULE	3RD MODULE
618A, B 634A, B, C, D 636A, B, C 638A, B, C (Note 2)	1	599A 657A	598A 656A	105B
	2			598A 656A
	4			617A
	6	599B 657B		105B
	7			598A 656A
	9	598A 656A		105B
	10			598A 656A
	11	599A 657A		617A
	12			
	13	599B 657B	598A 656A	59A
	14	599A 657A		
	15	599B 657B		

Notes:

1. For button arrangement on keys, refer to Table N.
2. Refer to Tables C, D, E, and F for set codes.

♦TABLE K♦
KEY ARRANGEMENTS—18-BUTTON DOUBLE LETTER (MD), TRIPLE LETTER (MD),
AND FOUR LETTER CODED SETS (NOTES 1 AND 2)

TELEPHONE SET		1ST MODULE	2ND MODULE	3RD MODULE
634DA,DAM,DAMS1 636CA,CAM,CAMS1 638CA,CAM,CAMS1 682AA,AAM,AAMS1 (Note 3)	1	635A5C	635G5C	111B
	2			635G5C
	4			658A
	6	635AD5C		111B
	7			635G5C
	11	635A5C		658A
	12			
	13	635AD5C	635G5C	76A
	14	635A5C		
	15	635AD5C		

Note 1. Refer to Table B for available set codes.

Note 2. For button arrangement on keys, refer to Table N.

Note 3. Refer to Tables D, E, F, and G for all set codes.

TABLE L
KEY ARRANGEMENTS- 30 BUTTON SINGLE LETTER (MD) CODE SETS (NOTE 1)

TELEPHONE SET		1ST MODULE	2ND MODULE	3RD MODULE	4TH MODULE	5TH MODULE
608B, C 635A, C, D 637A, C, D 639A, C, D (Note 2)	1	599A 657A	598A 656A	598A 656A	105B	105B
	2				598A 656A	
	3					598A 656A
	4					617A
	5					59A
	9				617A	
	10	599B 657B			105B	105B
	11				598A 656A	
	12					598A 656A
	13	598A 656A			105B	105B
	14				598A 656A	
	15					598A 656A
	16	599A 657A			105B	667B (MD) Trmtr
	17				598A 656A	
	18				617A	
	19				598A 656A	59A
	20	599B 657B				667B (MD) Trmtr

Note 1. For button arrangement on keys, refer to Table N.

Note 2. Refer to Tables C, D, E, and F for all set codes.

◆TABLE M◆
KEY ARRANGEMENTS—30-BUTTON DOUBLE LETTER (MD), TRIPLE LETTER (MD),
AND FOUR LETTER CODED SETS (NOTES 1 AND 2)

TELEPHONE SET		1ST MODULE	2ND MODULE	3RD MODULE	4TH MODULE	5TH MODULE
635DA,DAM,DAMS1 637DA,DAM,DAMS1 639DA,DAM,DAMS1 683AA,AAM,AAMS1 (Note 3)	1	635A5C	635G5C	635G5C	111B	111B
	2				635G5C	
	3					635G5C
	4					658A
	5				635AD5C	658A
	9	111B				
	10					111B
	11					
	12	635G5C				
	16	635A5C			111B	679A (MD)
	17				635G5C	
	18				658A	
	19				635G5C	76A

Note 1. Refer to Table B for available set codes.

Note 2. For button arrangement on keys, refer to Table N.

Note 3. Refer to Tables D, E, F, and G for all set codes.

◆TABLE N◆

KEY IDENTIFICATION

SINGLE LETTER CODE SETS A, B, C, D	598A OR 656A	599A OR 657A	599B OR 657B		617A	59A	667B	105B
DOUBLE, TRIPLE, AND FOUR LETTER CODE SETS AA, AAM, AAMS1, CA, CAM, CAMS1, DA, DAM AND DAMS1	635G5C	635A5C		635AD5C	658A	76A	679A	111B
Button Arrangement	P P P P P P	P P P P P H	C P P P P H	P P P P C H	S S S S S S S S S S S S	L L L L L L L L L L L L	OFF ON T V	B B B B B B

P — Pickup
 H — Hold
 C — Cutoff
 S — Signaling
 L — Lamp
 B — Blank

OFF
 ON Speakerphone
 T Transmitter
 V

