

TELEPHONE SETS
5300 TO 5400 SERIES
ORDERING APPARATUS AND PIECE PARTS

1. GENERAL

- 1.01 This section lists ordering information from 5300- to 5400-series telephone sets.
- 1.02 Replaceable piece parts peculiar to these sets are listed.
- 1.03 Component parts of these sets are also listed.
- 1.04 Parts with P numbers should be ordered with P number first. For example: P-18A974 Number Ring.

2. SUPPLIES

- 2.01 Apparatus and piece parts should be ordered according to Table A.

TABLE A

Telephone Set*	Housing	Hand Hold Cover	Ring Number	Anchor Cord	Handset	Mounting Cord	Adapter Dial	Dial**	Capacitor	Coil Induction	Ringer	Assembly Ringer Volume Control	Electron Tube	Bracket Tube	Key	Filter (Optional)
5302G-3F1	P-18A921	P-18A965	P-18A974	P-19A012	F1G-3	D3AY	59A	5M/6H	195A	101A	B1A	P-10E110				61S
5302G-3F4	P-18A921	P-18A965	P-18A974	P-19A012	F4A-3	D3AY	59A	5M/6H	195A	101A	B1A	P-10E110				61S
5302G-3G	P-18A921	P-18A965	P-18A974	P-19A012	G1A-3	D3AY	59A	5M/6H	195A	101A	B1A	P-10E110				61S
5304C-3F1	P-18A921	P-18A965	P-18A974	P-19A012	F1G-3	D3AY	59A	5M/6H	195A	101B	B2A	P-10E110				61S
5304C-3F4	P-18A921	P-18A965	P-18A974	P-19A012	F4A-3	D3AY	59A	5M/6H	195A	101B	B2A	P-10E110				61S
5304C-3G	P-18A921	P-18A965	P-18A974	P-19A012	G1A-3	D3AY	59A	5M/6H	195A	101B	B2A	P-10E110				61S
5306C-3F1	P-18A921	P-18A965	P-18A974	P-19A012	F1G-3	D3AY	59A	5M/6H	195C	101A	B3A	P-10E110	426A	P-19A011		61S
5306C-3F4	P-18A921	P-18A965	P-18A974	P-19A012	F4A-3	D3AY	59A	5M/6H	195C	101A	B3A	P-10E110	426A	P-19A011		61S
5306C-3G	P-18A921	P-18A965	P-18A974	P-19A012	G1A-3	D3AY	59A	5M/6H	195C	101A	B3A	P-10E110	426A	P-19A011		61S
5410AC-3F1	P-18A930	P-18A965	P-18A974	P-19A012	F1G-3	D4AN	59A	5M/6H	195B	101A ⁽¹⁾	B1A	P-10E110				61S
5410AC-3F4	P-18A930	P-18A965	P-18A974	P-19A012	F4A-3	D4AN	59A	5M/6H	195B	101A ⁽¹⁾	B1A	P-10E110			559C	61S
5410AG-3G	P-18A930	P-18A965	P-18A974	P-19A012	G1A-3	D4AN	59A	5M/6H	195B	101A ⁽¹⁾	B1A	P-10E110			559C	61S
5410BC-3F1	P-18A930	P-18A965	P-18A974	P-19A012	F1G-3	D6U3	59A	5M/6H	195B	101A ⁽¹⁾	B1A	P-10E110			559C	61S
5410BC-3F4	P-18A930	P-18A965	P-18A974	P-19A012	F4A-3	D6U3	59A	5M/6H	195B	101A ⁽¹⁾	B1A	P-10E110			559C	61S
5410BG-3G	P-18A930	P-18A965	P-18A974	P-19A012	G1A-3	D6U3	59A	5M/6H	195B	101A ⁽¹⁾	B1A	P-10E110			559C	61S
5410CC-3F1	P-18A930	P-18A965	P-18A974	P-19A012	F1G-3	D8M9	59A	5M/6H	195B	101A ⁽¹⁾	B1A	P-10E110			559C	61S
5410CC-3F4	P-18A930	P-18A965	P-18A974	P-19A012	F4A-3	D8M9	59A	5M/6H	195B	101A ⁽¹⁾	B1A	P-10E110			559C	61S
5410CC-3G	P-18A930	P-18A965	P-18A974	P-19A012	G1A-3	D8M9	59A	5M/6H	195B	101A ⁽¹⁾	B1A	P-10E110			559C	61S

*Sets equipped with a retractile handset cord will have the suffix R added to the code when ordering. For example: Set, Telephone, 5302G-3F1 will be coded Set, Telephone, 5302GR-3F1.

**Either 5M or 6H dial may be used.

⁽¹⁾ Equipped with a 39A shield.