


SERVICE

211-TYPE HAND TELEPHONE SETS

1. GENERAL

- 1.01 Reissued to add nontechnical changes to Fig. 1, 2, and Table A.



♦ Fig. 1—211J/L Hand Telephone Set Connections Used With 685A Subscriber Set ♦

**Reprinted to comply with modified final judgment.

◆ TABLE A ◆

**LINE AND RINGER CONNECTIONS
685A OR 686A SUBSET USED WITH
211J, L, N, OR P HAND TELEPHONE SETS**

WIRE OR LEAD		INDIVIDUAL OR BRIDGED	RING PARTY	NEGATIVE	POSITIVE
				RING STATION (NOTE 1)	
				1 AND 5	3 AND 6
Ringer Leads (Note 2)	R	L2	L2	G	L2
	BK	L1	G	G	L2
	S	K*	K*	A*	A*
	S-R	1	1	K*	K*
426A Tube Leads (3 elements) (686A only)	BK			K*	K*
	Y			L2	G
	R			G	L2

Notes:

- Reverse tip and ring for tip party service.
 - To silence ringer permanently, connect (R) and (BK) ringer leads to K on the terminal strip.
- * Terminal on 425E network.

TABLE B

ASSOCIATED APPARATUS

CLASS OF SERVICE	SUBSCRIBER SET
Individual Lines 2-Party Flat Rate 2-Party Message Rate (Ring Party Only) 4-Party Semiselective Multiparty Divided Code Regular PBX Stations 750A and 755A Keyless Stations	685A
4-Party Full Selective 8-Party Semiselective	686A


Note: No message rate or tip-party identification can be provided for tip-party station.

TABLE C

**61M FILTER CONNECTIONS
(NOTE)**

FILTER LEADS (NOTE)	FILTER LEAD TERMINATIONS	
	211J AND L	211P
BK	BK of Dial	BL of Dial
Y	Y of Dial	G of Dial
R	BK of Line Switch	1 of Line Switch

Note: The 211-type set is arranged for, but not equipped with, a 61M filter for radio frequency suppression. When this filter is required, remove lead from G of dial and 1 of the line switch on the 211 J and L sets and Y of dial and BK of the line switch on the 211P set and connect as shown in Table C.



◆ Fig. 2—211N/P Hand Telephone Set Connections Used With 685A Subscriber Set ◆