



Bulletin 700-82

Chicago 7, Illinois, U.S.A.

MONOPHONE TYPE 80 — CONVERSION TO 2-TONE COLOR —

1. CONVERSION

When the subscriber wishes his installed black type 80 Monophone converted to 2-tone, you need not replace the entire instrument, but only the housing.

1.1 Unscrew the 3 non-losable screws in the baseplate, remove the housing, and operate the hooklock to keep the line clear.

1.2 Inside the cover, essentially halfway between the hookswitch plungers, is a #6-32 \times 3/8" P.K.F.R.H. screw holding the cradle-hole cover (plunger stop). Remove this screw.

1.3 Transfer the cradle-hole cover, the screw, and the 2 plungers to the colored housing.

1.4 Place the new housing in position on the old instrument, and tighten the 3 non-losable screws in the baseplate.

2. ORDERING INFORMATION

Order colored housing as follows:

<i>Description</i>	<i>A.E.Co. catalog number</i>
Housing, sand beige	HO-20
Housing, dawn gray	HO-21
Housing, jade green	HO-22
Housing, classic ivory	HO-23
Housing, garnet red	HO-24
Housing, turquoise	HO-25