



**TABLE A**  
**LINE AND RINGER CONNECTIONS**  
**536A, B TELEPHONE SETS**

WIRE OR LEAD		INDIV OR BRIDGED	RING PARTY*	TIP PARTY IDENT	
				NORMAL CONNECTIONS	
				1000Ω	2650Ω
Ringer Leads (Note)	(R)	L2	L2	K	B
	(BK)	L1	G	G	B
	(S)	K	K	B	K
	(S-R)	A	A	B	G
Line Switch	S	L2	L2	A	A
Mtg Cord	Ring (R)	L2	L2	L1	L1
	Tip (G)	L1	L1	L2	L2
	Grd (Y)	G	G	G	G

\* Reverse tip and ring for tip party service.

**Note:** To silence ringer for all classes of service except tip party identification, connect S and BK ringer leads on K terminal of network. To silence ringer for tip party identification disconnect the R and S-R ringer leads for 1000Ω and BK ringer lead for 2650Ω and insulate and store.