

**MULTILINE - 4 AND 6 BUTTON
TELEPHONE SETS
SELECTION**

1. GENERAL

1.01 The telephone sets in Table A are capable of providing the services listed as factory supplied. Some services, such as 1A KTS, signaling, "I" hold, will require modification of the set.

1.02 Exclusion, if listed, indicates mounting cord leads are provided but requires the addition of a D-179935 Kit of Parts to 500 series

sets. This exclusion switch is provided on panel sets.

1.03 Refer to the service section listed for all wiring modifications.

1.04 Sets listed as capable of handset/headset operation are equipped with jacks but the headset must be separately ordered.

TABLE A

4- AND 6-BUTTON TELEPHONE SETS

TELEPHONE SETS SERVICES	TELEPHONE SETS																						
	540B 502-541-401	544A 502-541-402	544B 502-541-402	545B 502-541-403	563HB 502-541-404	564B 502-541-405	564C 502-541-405	564D 502-541-405	564H 502-541-405	564HBR, HDR 502-541-406	564HK, HL 502-541-407	565A 502-541-408	565B 502-541-408	565E 502-541-408	565G 502-541-408	565H 502-541-408	565L 502-541-408	565GK 502-541-414	565HK 502-541-415	565LK 502-541-416	565HD 502-541-410	565LD 502-541-412	
3-Line PU and Hold	•		•	•			•																
4-Line Pickup		•																					
5-Line PU and Hold					•	•			•	•	•		•			•			•			•	
6-Line Pickup												•			•			•					
4-Line PU and Hold										•					•			•			•		•
Cutoff Key															•			•			•		•
Exclusion				•	•							•	•	•	•	•	•	•	•	•	•	•	•
Speaker-phone															•	•	•	•	•	•	•	•	•
Handset/Headset					•																		
1A KTS	•	•	•	•	•	•	•	•	•	•		•	•	•	•	•	•	•	•	•	•	•	•
1A1-1A2 KTS	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Common Signaling					•				•	•	•							•	•				
I Hold					•						•								•				
2/4 Wire Operation																							
Station Busy Lamp*				•	•				•	•	•	•	•	•	•	•	•	•	•	•	•	•	•

* Requires KS-15724L1 diode.

TABLE A (Cont)

4- AND 6-BUTTON TELEPHONE SETS

TELEPHONE SETS SERVICES	568HB 502-541-420	568HT 502-542-406	568HF, HR 502-541-423	568HAA 502-541-425	1563HB 502-542-400	1564HK, HL 502-542-402	1565GK 502-542-403	1565HK 502-542-404	1565LK 502-542-405	568HT, 1568HT 502-542-406	2563HB 502-543-400	2564HL 502-543-402	2565GK 502-543-403	2565HK 502-543-405	2565LK 502-543-406	2568HAA 502-543-410	752A/B 502-736-401	754 502-736-402	1752A/B 502-737-401	2752A/B 502-738-401	2754A/B 502-738-402
3-Line PU and Hold																					
4-Line Pickup																					
5-Line PU and Hold	•	•	•	•	•	•		•		•	•	•		•		•	•	•	•	•	•
6-Line Pickup							•						•								
4-Line PU and Hold									•						•						
Cutoff Key									•						•						
Exclusion	•	•	•	•	•		•	•	•	•	•		•	•	•	•	•	•	•	•	•
Speaker-phone			•	•			•	•	•	•			•	•	•	•	•		•	•	
Handset/Headset					•						•										
1A KTS					•		•	•	•		•		•	•	•		•	•	•	•	•
1A1-1A2 KTS	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Common Signaling			•	•	•	•	•	•			•	•		•		•	•	•	•	•	•
I Hold			•		•	•		•	•		•	•	•	•							
2/4 Wire Operation	•	•	•	•							•	•				•					
Station Busy Lamp*				•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•

* Requires KS-15724L1 diode.