

# **BELL SYSTEM CODING FOR THE 200 SERIES**

## **COIN COLLECTORS**

**BSP: 506-310-100**

**Example: 233-H Coin Collector**

**First Digit: “2” = Uses 425B Network which would be in a 685 subscriber set.**

**Second Digit: “0” - Manual Post Pay, 5 Cent coin chute.**

**“1” - .10 Cent / Dial set / Post Pay**

**“2” - .10 Cent Prepay / 4 Spring dial shorting coin relay.**

**“3” - .10 Prepay / slow release single coil, dial shorting  
Coin relay. Coin collector has corrosion resistance  
Finish.**

**Third Digit: “0” - Basic Collector.**

**“2” - Washer rejection.**

**“3” - Pull bucket & washer rejection.**

**“4” - Pull bucket, washer rejection, and added security features.**

**First Suffix Letter = “C” – Manual service / U.S. coins only.**

**“D” – Manual service / U.S. & Canadian coins.**

**“E” – Dial, U.S. coins only, A-Type number plate.**

**“F” - Dial, U.S. & Canadian coins, A-Type number plate.**

**“G” – Dial, U.S. coins only, B-Type number plate.**

**“H” – Dial, U.S. & Canadian coins, B-Type number plate.**

**“L” - Local battery talking, common battery signaling.**

**Second Suffix Letter: Note that a second and third Suffix letter may exist as a result of set conversions performed at telephone company service facilities.**

**“N” – Uses a network**

**“R” – Spring or coiled handset cord.**

**“S” – 4 spring dial shorting coin relay.**

**“T” – Slow release, single coil, dial shorting coin relay.**

**Therefore a 233H coin collector is a set which uses a subset with a 425B network, is a .10 cent prepay with a slow release single coil, dial shorting coin relay, and the set has a corrosion resistant finish. A 233G coin collector would be the same, except it would only accept U.S. coins.**

© Jeff Lamb