

# Leich Telephone Set Model Number Identification

Model No.	Service	Style	Housing Material	Talking Eqpt	Speech Ckt & Misc. Features	Induction Coil	Ringer	Generator
<b>Telephone Sets – CB</b>								
62	CB/Dial	Desk	Bakelite	Handset	AST booster	#18	N	n/a
90A	CB/Dial	Desk	Bakelite	Handset	AST booster	#18	Y, bridged	n/a
90G	CB/Dial	Desk	Bakelite	Handset	AST booster	#18	Y, grounded	n/a
60	CB/Dial	Desk	Bakelite	Handset	AST booster using 8A/8B subset	N	N	n/a
61D	CB/Dial	Desk	Bakelite	Handset	series, DC receiver	N	N	n/a
91D	CB/Dial	Desk	Bakelite	Handset	series, DC receiver	N	Y	n/a
65A	CB manual only	Wall	Steel	Handset	AST booster	probably #18	Y, bridged	n/a
65B	CB manual only	Wall	Steel	Handset	AST booster	probably #18	Y, grounded	n/a
64A	CB dial, (not eqpd)	Wall	Steel	Handset	AST booster	probably #18	Y, bridged	n/a
64B	CB dial, (not eqpd)	Wall	Steel	Handset	AST booster	probably #18	Y, grounded	n/a
78	CB manual only	Wall	Steel	Handset	AST booster	probably #18	probably N	n/a
52A	CB dial, (not eqpd)	Wall	Steel	Trans & Rec	AST booster	probably #18	Y, bridged	n/a
52B	CB dial, (not eqpd)	Wall	Steel	Trans & Rec	AST booster	probably #18	Y, grounded	n/a
53A	CB manual only	Wall	Steel	Trans & Rec	AST booster	probably #18	Y, bridged	n/a
53B	CB manual only	Wall	Steel	Trans & Rec	AST booster	probably #18	Y, grounded	n/a
1C	CB manual only	Desk Stand	Steel	Trans & Rec	ST, IND coil in base	unspecified	N	n/a
1D	CB manual only	Desk Stand	Steel	Trans & Rec	series, DC receiver	N	N	n/a
51	CB manual only	Desk Stand	Steel	Trans & Rec	AST booster using 8A/8B subset	N	N	n/a
<b>Telephone Sets – Magneto</b>								
70A	LB	Desk	Bakelite	Handset	AST, w/o condenser	#19	N	N
70C	LB	Desk	Bakelite	Handset	AST, with condenser	#19	N	N
70R	LB	Desk	Bakelite	Handset	AST, DC PB to signal exchange	Note 1	N	N
72A	LB	Desk	Bakelite	Handset	AST, w/o condenser	N	N	N
72C	LB	Desk	Bakelite	Handset	AST, with condenser	N	N	N
92A	LB	Desk	Bakelite	Handset	AST, w/o condenser	N	Y	N
92C	LB	Desk	Bakelite	Handset	AST, with condenser	N	Y	N
92R	LB	Desk	Bakelite	Handset	AST, DC PB to signal exchange	probably #19	Y	N
86A	LB	Wall	Bakelite	Handset	AST, w/o condenser (70A+26 subset)	#19	Y	Y
86C	LB	Wall	Bakelite	Handset	AST, with condenser (70C+26 subset)	#19	Y	Y
86CD	LB	Wall	Bakelite	Handset	AST, with condenser (86C w/ PB switch)	#19	Y	Y
86D	LB	Wall	Bakelite	Handset	AST, w/o condenser, (86A w/ PB switch)	#19	Y	Y
77	LB	Wall	Steel	Handset	AST	probably #19	N	N
<b>Subsets</b>								
8A	Subset	Wall	Steel	none	unspecified IND coil	Y	Y, bridged	N
8B	Subset	Wall	Steel	none	unspecified IND coil	Y	Y, grounded	N
8R	Subset	Wall	Steel	none	no condenser or IND coil, used with 70R	N	Y	N
10A	Subset	Wall	Steel	none	ringer condenser only no IND coil	N	Y	N
11A	Subset	probably Wall	probably Steel	none	no IND coil "for wall mtg or on base of 90 telephone"	N	Y	N
26	Generator Box	Wall	Bakelite	none	used with 70 type to form 86 tel set	N	Y	Y

Note 1 - Catalog is unclear about whether the 70R telephone contains an induction coil but it probably does since 92R does.

Note 2 - AST indicates anti-sidetone circuit. ST indicates sidetone circuit.