

Western Electric Switchboard Lamps

Carbon Filament

		current	
code	volts	min	max

2C	15	.103	.12
2E	20	.09	.12
2F	12	.105	.12
2G	24	.075	.115
2J	24	.018	.033
2K	30	.09	.12
2R	18	.09	.12
2T	40	.034	.046
2U	24	.035	.048
2W	18	.035	.045
2Y	48	.03	.042

Tungsten Filament

A1	24	.033	.045
A2	24	.075	.105
B2	18	.036	.048
C2	36	.032	.044
E1	6	.033	.045
E2	6	.27	.31 (replaces 2H)
E3	6	.12	.16 (replaces 2H)
F1	4	.17	.21 (replaces 2A)
F2	4	.27	.31 (replaces 2B)
G1	8	.085	.10 (replaces 2P)
G2	8	.035	.05
H1	16	.27	.31 (replaces 2D)
J1	10	.23	.27 (replaces 2L)
K1	30	.033	.045
K2	30	.032	.044

51A 10 .035 .045 (for key phones)