

COIN STATION SETS

MAGNETO — SELECTION

1.00 INTRODUCTION

This section covers, in table form, the selection of coin collector sets for magneto lines and associated subscriber sets.

2.00 GENERAL

2.01 The general information in Table A contains the:

- Types of handsets or transmitters and receivers that are normally furnished, as well as the types that may be substituted.
- Types of subscriber sets that may be used with each coin collector.
- The number of generator bars in the various subscriber sets.

2.02 Coin collectors are not selected by class of service, as it is assumed that they will be used on individual lines as recommended.

TABLE A

Selection of Magneto Coin Collector Sets

Magneto Central Offices						Coin Collectors			Subscriber Sets	
									No. of Generator Bars*	
Handsets				Trans	Rec	Trans — Rec Type	Coins		3	5
F1	F2	F4	F5	635	706A		U. S.	U. S. and Canada	400CD 415CD 415H	400A 400K
				+	+	150	K	L	• or •	
				+	+	162	A	B	• or •	
				+	+	162	C	D	• or •	
						Handset Type				
	+		#			152	C	D	• or •	
	+		#			164	C	D	• or •	
+			#			182	C	D	• or •	

* Use 5-bar generators on loops over 800 ohms.

+ Recommended equipment.

Reasonable substitutes; should be used only when required for transmission reasons.

• Subscriber sets required.

NOTICE

This document is either
AT&T - Proprietary, or WESTERN
ELECTRIC - Proprietary

Pursuant to Judge Greene's Order of August 5, 1963, beginning on January 1, 1964, AT&T will cease to use "Bell" and the Bell symbol, with the exceptions as set forth in that Order. Pursuant thereto, any reference to "BELL" and/or the BELL symbol in this document is hereby deleted and "expunged".