

[illegible]

TABLE B
LINE AND RINGER CONNECTIONS

Wire or Lead		Individual or Bridged	Ring Party, All Classes of Service	Tip Party Flat Rate
Mounting Cord in Set		R	L1	L1
		G	L2Y	L2Y
		Y	GND	GND
Ringer Lead		R	E	E
		BK	K	K
		BK	L1	GND
Key Lead		BK	E	E
		R	R	R
		G	G	G
Mounting Cord at Connecting Block		Y	Y	Y
		R	R	R
		G	G	G
Line Wire at Connecting Block	Ring	R	R	R
	Tip	G	G	G
	Grd	Y	Y	Y

TABLE A
FILTER (Optional)

Type Filter	Filter Leads	Filter Lead Termination
61P or 61L	BK	BK of Dial
	Y	Y of Dial
	R	Filter Bracket Terminal; also, disconnect BR-Y lead from Y of dial and reconnect to filter bracket terminal

Fig. 1 — 305E, G Telephone Sets