

The No. 205 Type Hand Telephone Set is designed for use with anti-sidetone subscriber sets in No. 750A Private Branch Exchange systems.

When specified in the order these Hand Telephone Sets will be furnished equipped with a No. 61J Filter to suppress dialing induction into radio receiving sets.

The No. 205A, 205B and 205C Types are intended for use at key stations not arranged for routing central office trunk calls.

The No. 205D, 205E and 205F Types are intended for use at key stations arranged for routing central office trunk calls to and from keyless stations.

	Consists of					
Code No.	Hand Set Mtg.	Dial No.	†Cords		Hand Set	Recommended in Place of
205A-3 205B-3 205C-3 205D-3 205E-3 205F-3	E4-3 E4-3 E4-3 E4-3 E4-3	4HA-3 4HB-3 4HE-3 4HA-3 4HB-3 4HE-3	One D8E-9 One D8E-9 One D9A-9 One D9A-9 One D9A-9	*Three M1E *Three M1E *Three M1E *Three M1E *Three M1E *Three M1E	E1B-3 E1B-3 E1B-3 E1B-3 E1B-3	105A-3 105B-3 105C-3 105D-3 105E-3 105F-3

^{*} $5\frac{1}{2}$ inches long.

[†] When specified in the order will be furnished equipped with a D8F type cord of corresponding color assembled with a No. 274A type plug (274A-3 plug furnished unless otherwise specified) instead of the corresponding D8E type cord.